

MEI-7512 LED Codes



LED Codes	
	Mode Button
	LED On
	LED Blinks Off
	LED Flashing

Mode Button Operation	
	Press once to access Service Mode
	Press & Hold to access Set-up Mode
	Press twice to view audit data * Ensure tube cassette is <i>installed</i>
	Press twice to park the dispenser arms * Ensure tube cassette is <i>removed</i>

Amber LED Codes	
	Inhibited by VMC
1 x	Discriminator Error
2 x	Accept Gate Error
3 x	Separator / Tube Error
4 x	Dispenser Error
5 x	Low On Change

Green LED Codes	
	Changer OK
	Changer Faulty
After Pressing Mode Button	
	Slow Flash - In Set-up Mode/Service Mode
	Fast Flash - Message Available
Coin Accepted/Rejected	
1 x	Coin was Accepted
2 x	Coin was Rejected - Not Recognized
3 x	Coin was Rejected - Inhibited by Changer/Machine



888.396.8363 - Atlanta
800.248.1712 - Orlando

www.vendorsrepair.com

V
R
S

T
E
C
H

T
I
P
S